

● **Сортамент**

Номинальное сечение провода, мм ²	Провод марки МА		Провод марки МГ		Максимальная токовая нагрузка, А
	номинальный диаметр проволоки, мм	число проволок	номинальный диаметр проволоки, мм	число проволок	
1,5	0,52	7	0,32	19	10,0
1,5*	-	-	0,20	49	10,0
2,5	0,68	7	0,26	49	16,0
3,0	-	-	0,28	49	18,0
4,0	0,85	7	0,32	49	25,0
5,0	-	-	0,37	49	29,0
6,0	1,04	7	0,38	49	37,0
8,0	-	-	0,45	49	47,0
10,0	1,35	7	0,52	49	60,0
10,0*	-	-	0,30	140	60,0
16,0	1,04	19	0,64	49	92,0
16,0*	-	-	0,30	224	92,0
25,0	-	-	0,58	98	137,0
35,0	-	-	0,58	133	173,0
50,0	-	-	0,68	133	219,0
70,0	-	-	0,68	189	267,0
95,0	-	-	0,68	259	319,0
120,0	-	-	0,77	259	395,0
150,0	-	-	0,85	259	465,0
185,0	-	-	0,80	361	538,0
240,0	-	-	0,85	427	684,0
300,0	-	-	0,85	513	750,0
400,0	-	-	0,85	703	875,0